EB6500XKC

- Dual voltage power with premium features and GFCI (Ground Fault Circuit Interrupter) protection on duplex receptacles.
- 6500 watts maximum AC output
- Industrial applications and Commercial usage
- Suitable for rental applications

SPECIFICATIONS

MAXIMUM AC OUTPUT (WATTS)	6500
AC Voltage Available	120/240
MAXIMUM CONTINUOUS AC OUTPUT (WATTS)	5,500 7,000 (iAVR)
Max. Rated AC Amperage @ 120 V/240 V	45.8/22.9 (58.3/29.2 for 10 sec. iAVR)
GROUND FAULT CIRCUIT INTERRUPTER (GFCI)	Standard
FREQUENCY (HERTZ)	60
AUTOMATIC VOLTAGE REGULATOR	Standard iAVR (Intelligent Automatic Voltage Regulator)
DC Output Volts/Amps	N/A
Engine Type	Honda iGX390T2 OHV, 4-stroke, air-cooled
DISPLACEMENT	389 cc
STARTING SYSTEM	Manual recoil
Low Level Oil Alert System	Standard
AUTO THROTTLE	Standard
REMOTE START CAPABILITY	No
FUEL TANK CAPACITY (LITRES)	23.5
TRANSPORT WHEELS	2 Wheel standard
LIFTING HOOK	Standard

BATTERY	N/A
Approximate Running Time/Tankful (hrs)	6.9**/10.4****
Rated Fuel Consumption (Litres/Hour)	3.40**
Noise Level dB(A) (1.5 m to 7 m)	73**
Length (Without Handles and Wheels)	681 mm (26.8 in.)
Length (With Handles and Wheels)	1,051 mm (41.4 in.)
Width (Without Handles and Wheels)	530 mm (20.9 in.)
Width (With Handles and Wheels)	706 mm (27.8 in.)
Height (Without Lift-Hook)	719 mm (28.3 in.)
Height (With Lift-Hook)	773 mm (30.4 in.) standard
DRY WEIGHT	97.2 kg (214.3 lb.)
COLD CLIMATE TECHNOLOGY	Standard
Common Duplex Receptacle Specifications	40 amps/120 VAC continuous is available as combined total from these twin duplex AC receptacles. Maximum of 20 amps available from each GFCI duplex receptacle.
DC Charging Cable	-
High Capacity 120/240 VAC Twist Lock Receptacle Specs	This receptacle will supply 30 amps at 120 VAC continuously. This receptacle will supply 22.9 amps (5.5 kVA) at 240 VAC continuously
Distributor's Warranty (commercial use)	36-month
Distributor's Warranty (non-commercial use)	36-month

Models and/or colours may not be exactly as shown. Errors and omissions excepted. Specifications are subject to change without notice.

See your Honda Power Equipment dealer for details.

For optimum performance and safety, please read your owner's manual before operating your Honda product. Always wear the appropriate safety gear when operating your Honda.

®/TM — Trademarks of Honda Canada Inc. or used under licence from Honda Motor Co., Ltd. or third parties.